

Quantec Corridor Display

Part No. **QT608C**



Overview

- A 16 character x 2 line display used to indicate incoming calls in corridors, staff rooms, nursing stations, etc.
- Includes an onboard sounder and buttons to accept, scroll through and manually divert calls.
- Shows call type, call location and (depending on the device used to make the call) the User ID or name of the person calling.
- Highest priority calls are shown first with a message saying how many calls are waiting.
- Flash and sounder rates intensify to reflect the urgency of incoming calls.
- Adjustable contrast and volume controls.
- External sounder connection.



Technical Specifications

Power requirements	Nominal 24V DC (from Quantec Controller/Network)
Quiescent current	5mA (with back light off).
Indicators	2 line x 16 character backlit LCD display.
Controls	Accept (A); Scroll Up; Scroll Down. Adjust contrast; Adjust volume; Enable internal/external beeper.
Connections	Net +: Net -
Expansion connections	External sounder connection (current sink to the NET- line rated at 30 V, 30mA, 300 mW dissipation max.)
Onboard Sounder	Yes.
Onboard Infrared Receiver	No.



Product dimensions (mm)	146 W x 87 H x 35 D mm. Mount on a 35mm deep back box.
Construction & finish	Plastic.
IP Rating	IP40.
Weight	166g.
Operating conditions/temperature	-5°C to +40°C. Max relative humidity: 95%.

