

Quantec Addressable Call Point, Button Reset (No Remote)

Part No. **QT609**



Overview

- A programmable Quantec addressable call point.
- Includes a Call button, Reset button and red/green confidence light.
- Can make up to 5 levels of call - Standard, Ensuite, Help Required, Emergency, Presence & Attendance (dependent on configuration and ancillary devices used). Attack and Attendance calls can also be made if connected to compatible infrared receiver.
- Can be programmed to operate in a multitude of ways using a QT423 configurator.
- Connections provided for ancillary devices such as ceiling pulls, overdoor lights, infrared receivers and more.

Technical Specifications

Power requirements	Nominal 24V DC (from Quantec Controller/Network)
Quiescent current	Less than 3mA.
Alarm current	14mA.
Indicators	Red/green confidence LED.
Controls	Call button; Reset button.
Connections	Net +; Net -; R; G; L+; SW; IR; SLV.
Expansion connections	R; G; L+; SW; IR & SLV terminals allow the connection of optional dummy/extender overdoor lights, dummy/extender call points, dummy/extender ceiling pulls and dummy/extender infrared receivers.
Onboard 6.35mm Remote Jack Socket	No.
Onboard Sounder	No
Onboard Infrared Receiver	No.
Product dimensions (mm)	86 W x 86 H x 23 D mm. Can be mounted on a standard UK 25mm single gang flush or surface back box.



Construction & finish	Plastic.
IP Rating	IP41.
Weight	32g.
Operating conditions/temperature	-5°C to +40°C. Max relative humidity: 95%.

