HAYDON

Fire Detector Indicator & Fire 24V Relay

HAY-FIRE-DO

Fire Indicator Detector Operated

- Operating Voltage: 3VDC or 24VDC
- Nominal Current Consumption: 5mA
- Enclosure Material: Plastic
- Fits standard single gang plastic gang box: not supplied
- Dimensions: W.86 x L.86 x H.15mm
- Weight: 0.1kg
- Warranty: 3 years



HAY-FIRE-24R

Fire 24V Relay

- Operating Voltage: 24VDC ± 10%
- Nominal Current Consumption: 22mA
- Relay: Double Pole
- Relay Rating: 5A @ 250v AC
- Relay Coil Impedance: 1067 Ohms
- Enclosure Material: Plastic
- Dimensions: W.86 x L.86 x H.62mm (faceplate)
- Surface Back Box Supplied
- Weight: 0.2kg
- Warranty: 3 years



Haydon Marketing Limited, Unit 3, The Furlong, Berryhill Industrial Estate, Droitwich, UK, WR9 9AH
Website: www.haydonmarketing.com Email: enquiries@haydonmarketing.com
Telephone: 0044 (0)1905 772222 Fax: 0044 (0)1905 779555